4g LTE portable mifi router G4



Yifan Industry Co., Ltd

Room618, No.12 Gaodian Road, HuLi District, Xiamen,FuJian, China

Tel:+86 592 6101492

Fax:+86 592 5222813

Email: admin@yifanwireless.com



.Overview

Yeacomm G4 Mobile WiFi is a high-speed packet access mobile hotspot. It is a multi-mode wireless terminal for SOHO (Small Office and Home Office) and business professionals.

G4 supports the following standards:

- *Long Term Evolution (LTE) Frequency Division Duplex (FDD) Time Division Duplex(TDD)
- *Dual Carrier High Speed Packet Access Plus (DC-HSPA+)
- *High Speed Packet Access Plus (HSPA+)
- *High Speed Uplink Packet Access (HSUPA)
- *High Speed Downlink Packet Access (HSDPA)
- *Universal Mobile Telecommunications System (UMTS)
- *Enhanced Data rates for Global Evolution (EDGE)
- *General Packet Radio Service (GPRS)
- *Global System for Mobile communications (GSM)
- *G4 provides the following services:
- *LTE FDD packet data service
- *DC-HSPA+ packet data service
- *HSPA+/HSPA/UMTS packet data service
- *EDGE/GPRS packet data service
- *Short Message Service (SMS)

G4 is with color screen and easy to use, you can connect the router with the USB interface of a computer, or connect via Wi-Fi. In the service area of the LTE FDD /DC-HSPA+ /HSPA+ / HSPA/UMTS or EDGE/GPRS/GSM network, you can surf the Internet and send/receive messages/emails.It is with battery, you can use it at home, in the office or the way to travel, sharing the wifi with your friends.





\





2. Technical Specifications

2.1 Hardware information

Hardware Info		
Frequency (Frequency could be customize)	LTE FDD: B1/3 (B5/7/8/20 optional)	
	LTE TDD: B38/39/40/41	
	DC-HSPA+/HSPA+/HSPA/UMTS : 900 / 2100 MHz	
	850/900/1900/2100mhz(optional)	
	EDGE/GPRS/GSM:850/900/1800/1900Mhz	
	WLAN: 2.4GHZ	
Speed	FDD - LTE Downlink: 150Mbps, Uplink: 50Mbps TDD-LTE: Downlink: 150Mbps, Uplink: 50Mbps HSPA+: 42Mbps(download speed) 5.76Mbps(upload speed) HSUPA: 5.76Mbps (upload speed)/ HSDPA:7.2Mbps(download speed:) UMTS:384Kbps (download speed/upload speed) (it is cat4)	
LCD	TFT 1.44 Inch 128*128	
Button	1 Power 1 WPS ON/OFF	
SD card	UP to 32G	
WIFI	802.11 b/g/n	
Battery	2100mAh Lion	
Port	1 * Standard USIM 1*Micro SD 1 * Micro USB	
Antenna	Internal 1*WIFI 2*LTE	
Charger	Output : 5V DC±10%; Output : 1A Input : 100V~240V,50Hz~60Hz	
Working Temperature	-10°C to 45°C	
Working Humidity	5% - 65%	
Storage Temperature	-30°C to 80°C	
Storage Humidity	5% to 95%	

3



2.2 Software information


OS	Win7, Windows XP, Vista, Mac OS,Android,linux	
Language	Chinese & English	
Network connection Set up	APN management: create, delete and edit. Set up network connection (automatically connection)	
Wifi Sharing	Up to 10 sharing	
SMS	Writing/Sending/Receiving Sending/Receiving extra-long messages New message prompt	
Firewall setup	Firewall Switch Virtual Server ACL Service DMZ Service UPnP Service	
WIFI setting	SSID broadcasting and hiding Open system and shared key authentication 256-bit WPA-PSK and WPA2-PSK encryption Automatic adjustment of ratios	
Software installation	Automatic installation	
Contact Book	Supported	
Routing Settings	Supported	
Others	*Network connection settings: Automatic network selection and registration Manual network selection and registration Network status display: signal, operator name, system mode, and so on. *Selection of network connection types, for example: LTE Only 3G Only Auto	




3. Web Page

After you connect the router and PC via a USB data cable, the Web page is displayed on the PC desktops automatically. You can directly use the default settings (or configure APN on the Web page) and set up a network connection. Or you can set up via wifi connection. Enter: http://192.168.0.1

3.1 advanced setting




3.2 APN setting





3.3 SMS



4. Packing list

Packing list of the G4 as follow:

Item	Quantity
4g mobile wifi	1
Rechargeable Battery (2100 mAh)	1
USB Cable	1
User manual	1

6